## enel **\* way**



# Get going with the JuiceBox 32, your essential smart home charging station

JuiceBox 32 is a Level 2 smart home charging station with the essential features and power you need to charge your EV. It is ideally suited for older homes, condominiums, and residences with electrical circuits limited to 40 amps.

JuiceBox is the only line of charging stations that affords both direct user control and smart grid optimization, accessible through the Enel X Way App.

- · Control charging anywhere, anytime via our mobile app
- · Reduce your energy costs by scheduling charging when rates are low
- Select a cleaner electricity mix to reduce your emissions (in certain geographies)
- Participate in smart grid programs to further lower the cost of owning and driving your EV



enel \* way

### Why JuiceBox?

#### Up to 6x Faster Charging

Spend less time waiting for your EV to charge and more time enjoying the drive

#### Powered by Enel X Way App

Monitor and schedule charging with intuitive mobile app to save time and money

#### **Universal Compatibility**

SAE-J1772TM plug ensures compatibility with all EVs\*

#### **Cleaner Driving**

Optimize charging times and participate in smart grid programs to reduce emissions; ENERGY STAR®-certified

#### **Easy to Use and Install**

Small, lightweight enclosure; lockable, quick-release mount; weatherproof for indoor/outdoor installation

#### **See Charger Status**

Dynamic LED lights display WiFi connectivity and charging behavior

\*Tesla requires adapter

## enel **\* way**

#### 6.8 in/17.3 cm **JuiceBox 32 Specifications** enel \* way 8 > Safety Rated: 32A Max . CJ > Single phase input: nominal voltage **Electrical Characteristics** Ņ 110-240 VAC ~60 Hz 41 > Power: up to 7.7 kW (32A) at 240VAC Ω JuiceBox > 2 ft/0.6 m with NEMA 14-50 plug **Input Cable & Plug** > 2.5 ft/0.8 m hardwire pigtail 25 ft/7.6 m cable > **Output Cable & Connector** J1772 standard compliant > > Precision measurement of power, energy, voltage & current Automated notifications: time-of-use in effect, start of charge, end of charge, unit offline, > **Enel X Way App** unit back online, car not plugged in by a set time See Enel X Way App Data Sheet for more on convenient features > **Smart Grid Connectivity** Built-in WiFi connectivity (802.11 b/g/n 2.4 GHz) > > End-to-end AES-256-based encrypted protocols > 90-day, 15-minute interval data storage **Firmware** Over-the-air (OTA) upgradeable firmware > Persistent data storage upon power interruption **Emissions Reduction** Available via optional JuiceNet<sup>®</sup> Green software upgrade Dynamic LED lights show charging status: network connectivity, charging in progress, delaying charging, standby, charge complete/EV not drawing power > IP66: Weatherproof, dust-tight **Enclosure** > IK10: Resistant polycarbonate case > Quick-release wall mounting bracket included Built-in security lock and integrated cable management Operating Temperature: -40°F to 140°F (-40°C to 60°C) > Altitude > Up to 2000 m/6500 ft Main enclosure: H: 18.5 in/469 mm x W: 6.8 in/173 mm x D: 5.8 in/147 mm > Weight & Dimensions > 15 lbs/6.8 kg FCC Part 15 Class B, NEC 625 compliant, OCPP 1.6J, ENERGY STAR® > **Codes & Standards** > **OpenADR 2.0b compliant** > UL and cUL Listed Safety > 3-year limited product warranty (parts only) for use under normal residential operating Warranty conditions **Made in North America** From domestic & imported parts

JUICEBOX and Enel X Way App are registered trademarks of Enel X North America, an Enel Group company. Other product and company names mentioned herein may be trademarks or trade names of their respective owners.

@enelxwaynaf EnelXWayNA

- in enelxway
- O @enelxwayna